



Instruction on how to upgrade MyM Pro- 3T/6T and MyM Pro-3S/6S to firmware version 2.1

***It is extremely important that you follow the instruction below, otherwise the upgrade will fail!
Download the zip file, unzip and save files to a directory at your PC.***

NOTE! Please stop all analogue decoding and remove CA module before starting the upgrade procedure. Make sure that all programs are unselected in Service management i.e. click boxes are grey marked.

Services

Service Selection

Ch-1	Ch-2	Ch-3	Type	Name	Provider	Input	SID
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		TV4 Linköping	TV4 AB	Ant 1	6160
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		TV6	Viasat Broadcasting UK	Ant 1	1070
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		TV4 Film	TV4 AB	Ant 1	1130
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		TV11	TV4 AB	Ant 1	1140
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		CNN	Turner Broadcasting	Ant 1	1160
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		TV4 Fakta	TV4 AB	Ant 1	1220
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Boxer Navigator	Boxer TV Access AB	Ant 1	65534
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Sjuan Linköping	TV4 AB	Ant 1	7280
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		24Corren	NT Media AB	Ant 2	8050
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		TCM	Turner Entertainment	Ant 2	1200
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		SILVER	Nonstop Television AB	Ant 2	790
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Axess TV	Axess Publishing AB	Ant 2	800
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Boxer Navigator	Boxer TV Access AB	Ant 2	65534
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Kanal Global	DTU Television AB	Ant 2	770
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		TV4 Sport	TV4 AB	Ant 2	750
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		BBC World News	BBC Worldwide Ltd	Ant 2	3200
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Animal Planet	Discovery Communications	Ant 2	3220
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Discovery Science	Discovery Communications	Ant 2	3230
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Disney XD	Disney	Ant 2	3240
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Showtime	Nonstop Television AB	Ant 2	3250
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		TNT	Nonstop Television	Ant 2	3260
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Star!	Nonstop Television AB	Ant 2	3270
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		C+ Series	C More Entertainment AB	Ant 2	3280
<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>		Cartoon Network	Turner Networks	Ant 2	3330

A) Connect your PC to the MyM Pro (direct or through switch) unit that you want to upgrade. **NOTE! Use Internet Explorer because that web browser is approved.**

B) Unselect all services (as picture ahead) and remove CA modules.



C) Select the menu "System options" and browse for the file FW 2.1 at your PC and click on upload.

D) If the upload is succeeded you shall now get a picture as below

Overview Input Output Service Management CI System Options

Message

File	Build	Message
Firmware	1.450	Upload complete!
UI	1.200	Upload complete!
FPGA	1.200	Upload complete!
Audio DSP	1.010	File already exists
Video DSP	1.010	File already exists

Restart

Copyright © A2B Electronics AB



E) Click on "Restart" button and **wait 2 minutes**. Click on "Overview menu" and you shall now get a view like below.

MyM Pro WEB Configurator



Overview Input Output Service Management CI System Options

Current settings Installation overview Software options

Current settings

Module identification

Serial number:	0420011111400021
Hardware revision:	2202
Name:	TV4 unit
Description:	Tv4,TV6, Animal
Position:	Upper

Configuration

Firmware version:	2.1
Bootloader version:	0300
Input:	Tuner DVB-T

Status

Tuner1 locked:	Yes
Tuner2 locked:	Yes
Uptime	0d 0h 1m 20s

Network

IP Address:	172.19.99.94
Netmask:	255.255.0.0
Gateway:	172.19.0.1

Copyright © A2B Electronics AB

If you experience any problems with the installation or the new software, please contact our customer support or call +46 (0)141 229100:

Olle Carlsson
Thomas Wernhede

Email : support@a2b.se