



Instruction on how to upgrade MyM to FW 2.1

It is extremely important that you follow the instruction below, otherwise the upgrade will fail!

1. Downloading the FW 2.1 to your PC from the A2B Internet site
 - Go to <http://www.a2b.se/index.php?id=22>
 - Select Firmware (login) and do the login
 - Click on FW 2.1 to download the firmware and unzip the file
2. Connect your PC directly to the RJ-45 port of the MyM unit that you want to upgrade
3. Start a web browser (Internet Explorer, Firefox, Opera etc.)
4. Type IP adress 192.168.0.20
5. Click on the Upload Menu Tab and browse to locate the FW 2.1 file
6. Click on UPLOAD and wait for the message "Upload completed"
7. Do a power reset of the MyM to make the new firmware version take effect.

NOTE! If upload has failed i.e. no "Upload completed" message appear, please try once again before doing a power reset.



When this is ready the view in the Upload menu could be as showed below:

MyM Web Control Interface



Upgrade

Upgrade the MyM with the latest firmware or software options.

Note : Do not disconnect power to the unit during the update. The **MyM** needs to be restarted after the upgrade has completed.

Locate and select the upgrade file from your hard disk:

File list

File	Version	Build	Image
UI for ALCES	M2RELEASE1	2.1	0.580 [delete]
Translations	M2RELEASE1		1.040 [delete]
Audio DSP	M2RELEASE1		1.000 [delete]
Video DSP	M2RELEASE1		1.000 [delete]
FPGA	M2RELEASE1		1.000 [delete]
Firmware for M2	M2RELEASE1	2.1	0.830 [delete]

Copyright © A2B Electronics AB

It's important that the marked files now are present in the file list. If not you should go through the Upgrade procedure again.

Other files shown are depending on what firmware versions you have had before upgrading the unit to FW 2.1

If you experience any problems with the installation or the new software, please contact our customer support or call +46 (0)141 229115:

Olle Carlsson

Thomas Wernhede

Email : support@a2b.se