

Upgrade MyMPro (not Micron) from FW 2.1 (or earlier) to FW3.1.1srA2



Note 1

MyM Pro T (tuner 037) can't be upgraded without change of tuner board. Upgrading will crash the unit and can only be restored at the repair center.

Note 2

After upgrade to FW 3.1.1 and use with CI modules following has to be done after inserting the CAM's and selected the services in Service management:

1. Go to Output menu.
2. Go to Decoder 1 and change Video conversation from Ignore to Auto and click Save. Do the same for Decoder 2 and Decoder 3.
3. Reboot unit and wait for WEB UI to update ie don't make anything in web browser before it has restarted itself

Upgrade instruction

1. Write a note of the unit IP address.
2. If the unit is without input signal:
Change "Output => Advanced => Video Watchdog" to OFF for Ch1, Ch2 and Ch3 before next step
3. Upload the file **ALCES_2.1-Upgrade.bin**
4. Reboot the unit from the web ui. Wait for the automatic web ui refresh or wait two minutes to continue.
5. Upload the <Entitlement file> for the unit (order this from support@wisi.se)
6. Reboot the unit from the web ui. Wait for the automatic web ui refresh or wait two minutes to continue.
7. Upload the file **ALCES_3.1.1srA1.bin**
8. Reboot the unit from the web ui. Wait for the automatic web ui refresh or wait two minutes to continue.
9. Download the file **Default_Configuration_File_MYMPro.backup**
10. Restore the original IP address from 192.168.0.20 either using the application **IP_Supporter.exe** (downloadable from www.wisi.se) or attaching to the same subnet (192.168.0.x)
11. Setup and restore the original configuration